



KB2LJJ
Radio Mods Database



SPECIFICATIONS

- 1. Antenna Coupler
 - Frequency range 8 amateur bands from 3.5 to 29.7 MHz
 - Input impedance 50Ω
 - Output impedance 20 to 300Ω, unbalanced.
 - Through power 150W max. (3.5 MHz band, 120W)
 - Insertion loss Less than 0.5dB at optimum match.

- 2. SWR Meter
 - Frequency range 3.5 to 29.7MHz
 - Max. power 150W
 - Measurable range 1.0:1 to 10:1
 - Min. power required 2W

- 3. General
 - INPUT Connector UHF type (50Ω)
 - ANT Connector UHF type (50Ω)
 - GND Wing nut and STUD.
 - Dimensions H. 60mm (2-3/8")
W. 152mm (6")
D. 159mm (6-1/4")
 - Weight 1.6kg (3.5 lbs) approx.
- NOTE: The circuit and ratings may change without notice due to developments in technology.

SCHEMATHEEK
Beh. T. Hultermans
Postbus 4228
5804 EE Eindhoven

