








(5) Cancelling DTMF/CTCSS tone squelch temporarily



While DTMF/CTCSS tone squelches are set, push **00** to cancel them.

Both DTMF and tone squelch are set.

While squelch is cancelled (**00** appears)
While **00** appears, push **00**, **00** disappears and the squelch condition returns.

Push **00** while the **00** and decimal point appear. (Indicates that the squelch is cancelled)

once decimal point disappears

twice **00** only appears

While the decimal point exists (indicating the squelch is cancelled), push the **00** key.

The decimal point disappears.

Also, while the **00** exists, turn the power OFF then ON again to make the **00** disappear.

(6) Busy Channel Lock Out

During DTMF/CTCSS tone squelch setting, if a carrier with an unmatched tone or code is received or if the PTT is pushed, and an invalid operation beep sounds where transmission cannot take place, Busy Channel Lock Out has been set by your Dealer. Transmit can take place when the carrier disappears or when **00** appears in the LCD.